

PG2200i

2.2 Kw Petrol Inverter Generator

Features &

Accessories:

12V DC cables
Hour meter
USB Charger 5V, 1A; 5V, 2.1A
Plug Spanner
Rubber foot x 4
Engine Smart Control



NZ BASED
BACKUP



GREAT FOR
THE HOME



Inverter generator producing “clean or pure sine wave” power. Suitable for use with all tools and appliances. This model has maximum output of 2.2Kw, is lightweight, easily carried and very quiet.

This specification sheet does not constitute a contract or offer for sale. For the most up-to-date and specific product information, please contact our authorized representatives or visit our website. All product names, logos, and trademarks are the property of their respective owners and are used for identification purposes only.

GENERATOR

| | |
|----------------------|----------|
| Rated Frequency (Hz) | 50 |
| Rated voltage (V) | 230 |
| Rated output (kW) | 2.0 |
| Maximum output (kW) | 2.2 |
| Rated current (A) | 8.69 |
| Power factor (φ) | 1.0 |
| Phase | Single |
| DC output | 12V/8.3A |

ENGINE

| | |
|-------------------------------------|-----------------------------|
| Engine type | 1 cylinder, 4 stroke, OHV |
| Displacement (cc) | 98 |
| Ignition system | CDI |
| Spark plug | F6TC, F6RTC, BPR6ES |
| Starting system | Recoil |
| Lubricating system | Splashed |
| Lubricating oil | SAE 10W-30, Synthetic 5W-30 |
| Oil capacity (l) | 0.35 |
| Fuel type | 91 Unleaded gasoline |
| Continuous run time @ 50% load (hr) | 6.5 |
| Cooling system | Forced Air |
| Noise level (dB/7m) | 58 |
| Fuel tank capacity (l) | 5.6 |

PACKAGING

| | |
|----------------------------------------|-----------------|
| Outer carton dimensions (L x W x H mm) | 550 x 360 x 520 |
| Machine dimensions (L x W x H mm) | 495 x 300 x 460 |
| Net / gross weight (kg) | 20 / 22 |



9 421034 714106